

### NC8 and Accessories

- 1 Contactor
- 2 Mechanical interlock block
- 3 Contactor
- 4 Side mount aux
- 5 Side mount aux
- 6 Thermal overload relay
- 7 Front mount aux
- 8 Front mount aux
- 9 Pneumatic timers
- 10 Surge arrester block
- 11 Bus bar
- 12 Bus bar



3



4





8



9



**Quick selection table**

Frame size		9A	12A	18A	25A	32A	38A	
3-pole contactors								
	Auxiliary contacts	1NO+1NC	NC8-09	NC8-12	NC8-18	NC8-25	NC8-32	NC8-38
		2NO+2NC	NC8-0922	NC8-1222	NC8-1822	NC8-2522	NC8-3222	NC8-3822

Ratings/IEC/EN 60947-4-1		kW	A	kW	A	kW	A	kW	A	kW	A	kW	A
AC-1			25		25		32		40		55		55
AC-3	220V/230V/240V	2.2	9	3	12	4	18	5.5	25	7.5	32	9	38
	380V/400V	4	9	5.5	12	7.5	18	11	25	15	32	18.5	38
	415V	4	9	5.5	12	9	18	11	25	15	32	18.5	38
	660V/690V	5.5	6.7	7.5	9	9	10.6	15	17.3	18.5	21.9	18.5	21.9

Ratings/UL508		hp	A	hp	A	hp	A	hp	A	hp	A	hp	A
Continuous current (FLA)			25		25		32		40		50		50
Single phase	110V/120V	0.5		0.75		1		1.5		2		2	
	230V/240V	1		2		3		3		5		5	
Three phases	200V/208V	3		3		5		7.5		10		10	
	230V/240V	3		3		5		7.5		10		10	
	460V/480V	5		7.5		10		15		20		20	
	575V/600V	7.5		10		15		20		25		25	